

BEFORE YOU BEGIN

WARNING

Make sure power is **OFF** at the electrical panel before starting installation or any maintenance. Indoor installation only unless otherwise noted.

SAFETY

This fixture must be wired in accordance with local electrical codes and ordinances. All work should be done by a qualified electrician.

NOTE

Read all instructions before installing. Keep this sheet for future reference.

TOOLS REQUIRED

Saw · measuring tape · wire stripper · screwdriver · wire nuts.

INSTALLATION

- 01 Turn power OFF at the electrical panel.
- 02 Remove mounting bracket from fixture and mount onto ceiling.
- 03 Select CCT on the back of the fixture, remove protective plastic lens protector
- 04 Wire-nut connections: black to black, white to white, ground to green
- 05 For 0–10 V dimming, connect **purple (DIM+)** and **pink (DIM-)** to the dimmer leads. (FIG. 2)
- 06 Raise fixture onto ceiling and click into the mounting bracket
- 07 Restore power and verify operation.

0–10 V DIMMING WIRE

<input type="checkbox"/>	Line / Hot	BLACK
<input type="checkbox"/>	Neutral	WHITE
<input type="checkbox"/>	Ground	GREEN
<input type="checkbox"/>	Dim +	PURPLE
<input type="checkbox"/>	Dim -	PINK

FIGURES

